

Getting Started

Getting Started with butt - broadcast using this tool

Install *butt* - broadcast using this tool

For this guide we'll be using butt. You can download butt from their [website](#).

Configure *butt*

1. Launch butt
2. Click "Settings" to open the settings dialog



3. Under the "Server" section, click the "Add" button.

Getting Started

butt settings

Main Audio Stream Record TLS DSP GUI Donate

Server Settings

Server

ADD EDIT DEL

Stream Infos

ADD EDIT DEL

Log File

Configuration

Import... Save Export...

Check for updates

4. Set the server type to Icecast and enter your server details. Enter your first "Server Port" into the "Port" box. For example, if your "Server Ports" section says "7000, 7001 (SSL)", you would enter 7000 as your port. When you're done, press "Add".

Getting Started

Add Server

Name:

VosCast Stream

Type

☐ ShoutCast

☒ IceCast

SSL/TLS

☐ Use SSL/TLS

Revoke certificate trust

Address:

s1.vocast.com

Port:

7000

Password:

.....

Show

IceCast mountpoint:

stream

IceCast user:

source

Cancel

ADD

5. Under the "Stream Infos" section, click the "Add" button.

Getting Started

butt settings

Main Audio Stream Record TLS DSP GUI Donate

Server Settings

Server

VosCast Stream

ADD EDIT DEL

Stream Infos

ADD EDIT DEL

Log File

Configuration

Import... Save Export...

Check for updates

6. Enter your station name and details. When you're done, press "Add".

Getting Started

Add Server Infos

Name:

Station Name

Description:

The best station

Genre:

Jazz

URL:

https://voscast.com

ICQ:

IRC:

AIM:


☐ Make server public

Cancel

ADD

7. Go to the "Audio" tab, select the audio device you want to stream, and set your bitrate. For most people, the default device is the device you should select.

Getting Started



The screenshot shows a window titled "butt settings" with a tabbed interface. The tabs are: Main, Audio (selected), Stream, Record, TLS, DSP, GUI, and Donate. The "Audio" tab is active, displaying three sections of settings:

- Main Audio Settings:**
 - Audio Device: Default PCM device (default)
 - Channel: Stereo
 - Samplerate: 44100Hz
- Streaming:**
 - Codec: MP3
 - Bitrate: 128k
- Recording:**
 - Codec: MP3
 - Bitrate: 192k


8. Go to the "Stream" tab and choose how you want titles set. The option you choose will depend on what you're broadcasting, so choose the best option for your needs.

Getting Started

butt settings

Main Audio **Stream** Record TLS DSP GUI Donate

Update song name from file



☐ Activate ☐ Read last line instead of first

Update song name from application

▼

☐ Activate

Update song name manually

Streaming

☐ Start streaming after launch

Start if signal is present for seconds

Stop if signal is absence for seconds

9. Click the play button to begin broadcasting.

Getting Started



Unique solution ID: #1017

Author: Bryan

Last update: 2020-07-21 17:02